

For A Better Inspection Tool

Parameter Setting Instruction for V55

Parameter:

V55				
	Brightness	Contrast	Hue	Saturation
OD3.9mm	100	140	0	70
OD4.3mm	110	140	0	85
OD5.5mm	100	120	0	70
OD8.0mm (2-7cm)	130	120	0	70
OD8.0mm (10mm)	100	140	0	70
OD8.0mm (8-infinity)	100	140	0	70
OD6.5mm (7mm)	100	140	0	70
OD6.5mm (2-7cm)	110	120	0	70
OD12mm (8cm-infinity)	100	95	0	90
OD16mm (8cm-infinity)	100	140	0	70
OD20mm 3.7V (8cm-infinity)	110	140	0	70
OD20mm 12V (8cm-infinity)	115	140	0	70
OD25mm (2-5cm)	125	140	0	70
OD25mm (8cm-infinity)	125	140	0	70

Setting Instruction:

- Step 1. Under the preview mode, press the "OK" key to enter MENU mode.
- Step 2. Under MENU mode, press ▲ / ▼ key to select "Video Format", then press "OK" key to start "TV Output".
- Step 3. Press ▲ / ▼ key to select NTSC or PAL, then press "OK" key to decide video format and enter FACTORY SETUP mode to set the parameter.
- Step 4. Under FACTORY SETUP mode, press ▲ / ▼ key to select the item which is going to be adjusted, then press "OK" key to start parameter setting.
- Step 5. Press ▲ / ▼ key to adjust the parameter value, then press "OK" to Confirm.



ADRONIC